

PERLA VIDEO

Video intercom for X1 and XIP systems

CAME  BPT



FEATURES

- Lock release button
- Audio speakerphone
- 3.5" LCD display
- Two keys for activating the auxiliary/porter call
- Self-inserting video of entry panels with cyclic selection
- Ringtone volume setting keys
- Exclude ringtone and give LED alert
- Colour saturation and screen brightness settings
- Up to 8 intercom calls
- "Panic" button for emergency call to the porter
- Program ringtones depending on the type of call
- Video bouncing function among indoor receiver during simultaneous calls
- Master/Slave function

PEV BI 62100180

TECHNICAL SPECIFICATION

MODELS	PEV BI
Dimensions (mm)	145 x 170 x 31
Power supply by BUS (V)	15 ÷ 20 DC
Absorption by BUS (mA)	200
Consumption in stand-by mode (mA)	<1
Operating temperature (°C)	+5 ÷ +40
Protection rating (IP)	30
Video standard	PAL/NTSC
Display	3.5" TFT LCD
Colour	White

ARTICLE / CODE DESCRIPTION

PEV BI
62100180

Video intercom with 3.5" LCD display, 2 programmable AUX keys - white.

Surface mounted monitor with 3.5" colour LCD display. The keys for ringtone adjustment, colour saturation adjustment and brightness are on the left, while the keys for making up to 8 intercom calls and the "Panic" button for emergency requests to the porter are on the right. The main keys are clearly visible and backlit, allowing door opening and activation of communication, while the central dial is for managing the 2 auxiliary commands and self-inserting entry panel videos, plus excluding the ringtone (with LED signaling when the latter is excluded). It is equipped with a Master/Slave function and a video relaying between extensions function for simultaneous calls. It comes with a bracket for installing in a horizontal or vertical 503-type box and in a Ø 60 mm round box. Compatible with the X1 and XIP systems.

